## LOW COST TOGGLE FOR WET & DUSTY ENVIRONMENTS

These toggle switches are rugged, high performance sealed switches designed for use under severe conditions found in heavy equipment, industrial control, marine and appliance applications. The T7 series is sealed to both IP68S and IP69K. OTTO's front panel seal is accomplished with an O-ring under the bat handle. However, now a secondary visible bushing seal is offered as an option.

T7 toggles are offered in single and double pole configurations. A choice of models are offered to handle power levels to 16 amps, 0.5HP and low level electronic switching applications.


These toggles feature positive detent action for safe switching operation. In conjunction with the unique OTTO snap-action switch mechanism, the T7 offers non-teasible contact transfer.

High contact pressure and superior contact wiping action of the OTTO design makes the T7 an excellent choice for switching loads from logic level up to 16 amps.

Mounting hardware provided includes two hex nuts, one lockwasher and one keyway washer. An optional panel seal is available, P/N 710196, MIL. P/N M5423/16-01.

## **Features:**

- Sealed to IP68S and IP69K
- Switches up to 16 amps
- Withstands extreme shock & vibration
- Positive detent, non-teasible contact transfer
- 2 & 3-position, momentary & maintained action
- **Choice of terminal styles**
- **UL recognized & CSA certified**
- **RoHS/WEEE/Reach compliant**
- Black matte finish available. Contact factory.







Standard Characteristics/Ratings:							
ELECTRICAL RATINGS:							
Load	Sea Level @ 28VDC or 115VAC	Cycles					
Resistive	16A	25,000					
Resistive	10A	50,000					
Inductive	10A	25,000					
Motor	0.5 HP	25,000					
DWV	1050Vrms	N/A					
Low Level	10mA max @ 30mV max DC Resistive for 50,000 cycles						
Electrical Life:	See Rating Chart						
Mechanical Life:	100,000 cycles						
Seal:	IP68S and IP69K						
Operating Temp Range:	-30°C to +85°C						
MATERIALS:							
Case:	Thermoplastic						
Bushing:	Anodized aluminum alloy						
Toggle:	Stainless steel						
Terminals:	Brass						
Contacts:	Fine silver/silver cadmium oxide						
Low Level:	Gold over silver						
Terminal Hardware:	6-32 screw when applicable T7 recommended Quick Connect terminals: AMP 60253-2 for 12-16 AWG AMP 42100-2 for 14-18 AWG						
Mounting Hardware:	Hex nuts, lockwasher, key way washer						

<b>T7</b>	<b>PART</b>	NUMBER	CODE

T7-	<b>-X</b>	X		X		X	X	X	
			_		/	/		_	
Circuitry	Terminal Style	Contact Rating		Circuit Made With Actuator At:			Toggle St	yle	Button Color*
1. 1 Pole 2. 2 Pole	1250" Q.C. 2. Screw	<ol> <li>Std.</li> <li>Low</li> </ol>	ı	Keyway Side	Center	Opposite Keyway	1. Bat Hand		1. Red 2. Black
	3. Solder 4. PC Pin	Level	A. B.	ON ON	NONE	OFF ON	(consult fa	tton	3. Orange 4. Yellow
	(consult factory)		C. D. E.	(ON) (ON) (ON)	NONE NONE OFF	OFF ON (ON)	4. Rocker Br 5. Bat Hand Bushing S	le With	5. Green 6. Blue 7. Purple
			F. G. H.	ON (ON) OFF	OFF OFF NONE	ON ON ON			8. Gray 9. White
			J. K.	OFF ON	NONE OFF	(ON) (ON)		t	Only applicable to Toggle Styles
NOTE: ( ) denotes momentary action.								3 & 4; otherwise omit.	

\*See Lockout Configuration Codes on page 208

T7 Connector P/N C801765